
ATM Forum Document Number: ATM Forum/95-972

Title: Parameter Values for Satellite Links.

Abstract:

We show that Xrm is the key parameter which affects performance on satellite links. With current 8-bit XRM field, the maximum throughput on satellite links is limited to a few Mbps even on 155 or 622 Mbps links. The problem can be fixed by extending the field size to 32 bits.

Source:

Raj Jain, Shiv Kalyanaraman, Sonia Fahmy and Fang Lu
The Ohio State University

Raj Jain is now at Washington University in Saint Louis, jain@cse.wustl.edu <http://www.cse.wustl.edu/~jain/>

The presentation of this contribution at the ATM Forum is sponsored by NIST.

Date: August 6-11th, 1995

Distribution: ATM Forum Technical Working Group Members
(Traffic Management)

Notice: This contribution has been prepared to assist the ATM Forum. It is offered to the Forum as a basis for discussion and is not a binding proposal on the part of any of the contributing organizations. The statements are subject to change in form and content after further study. Specifically, the contributors reserve the right to add to, amend or modify the statements contained herein.

The ABR specification is designed for LANs, WANs as well as ATM over Satellite networks. The effects of the round trip delay become clear in satellite networks.

We have simulated a bidirectional one-source configuration with a satellite link. Of the parameters Xrm, XDF, TOF and RDF, Xrm is the most significant parameter and the other parameters, notably XDF have little or no effect in such networks.

Xrm is designed to protect against a broken network. But, at small values like 32 or 256 (the maximum value allowed currently), the ACR goes down to zero almost vertically and exhibits oscillations in the steady state.

From simulation, Xrm follows the relationship:
$$Xrm = N * PCR * RTTQ / Nrm$$

where

N = number of active sources

RTTQ = Maximum Round Trip Time including propagation, transmission and queueing.

Hence, X_{rm} needs to be chosen considering one round trip delay. The optimum values for satellite links are not even allowed in the current specification which allows only an 8-bit field for X_{rm} .

We note, that increasing N_{rm} to compensate for X_{rm} only reduces the frequency of feedback from the network. Hence, with a view to accommodating long round trip time networks, we propose a 32 bit field for X_{rm} .

Simulation results will be presented at the meeting.